

EECS 861
Homework #7

1. Determine whether the following functions can be the autocorrelation function for a WSS real values random process (YES or NO):

- a. $2\delta(\tau) + \cos(2\pi 100\tau)$
- b. $5 \text{rect}(\tau - 2)$
- c. $3\Lambda(\tau)$
- d. $4 e^{-10|t|}$
- e. $1000\text{sinc}(1000\tau)$
- f. $16 e^{\frac{-\pi\tau^2}{16}}$

2. $X(t)$ and $Y(t)$ are wide sense stationary, independent, zero mean, and jointly Gaussian random processes

$Z(t) = X(t)\cos(2\pi f_c t) + Y(t)\sin(2\pi f_c t)$ with f_c a constant and $R_{XX}(\tau) = R_{YY}(\tau)$

- a. Find $E[Z(t)]$
- b. Find $R_{ZZ}(\tau)$

3. Find the $E[X(t)]$ and $\text{Var}[X(t)]$ for a wide sense stationary random process with the following autocorrelation functions:

- a. $R_{XX}(\tau) = 4 e^{-10|\tau|}$
- b. $R_{XX}(\tau) = 9 + 4 e^{-10|\tau|}$
- c. $R_{XX}(\tau) = 16 e^{\frac{-\pi\tau^2}{16}}$
- d. $R_{XX}(\tau) = 9 + 16 e^{\frac{-\pi\tau^2}{16}}$

4. $X(t)$ is a wide sense stationary Gaussian random processes with $R_{XX}(\tau) = 10 e^{-10|\tau|}$.

- a. Find $E[X(0.1)]$, $\text{Var}[X(0.1)]$, $E[X(0.2)]$, and $\text{Var}[X(0.2)]$
- b. What is the distribution of $X(0.1)$, i.e., name of pdf and its parameters?
- c. Find $P(X(0.1) > 4)$
- d. What is the covariance matrix for $X(0.1)$ and $X(0.2)$?
- e. What is the joint distribution of $X(1)$ and $X(2)$, i.e., name of pdf and its parameters?
- f. What is the correlation coefficient between $X(0.1)$ and $X(0.2)$?
- g. Find $P(X(0.2) > 4 | X(0.1) = 3.5)$
- h. Approximate $P(X(2) > 4 | X(0.1) = 3.5)$

Hint: Check the result for part g. with **Study of the Conditional probability $P(X(t+\text{Tau}) > L | X(t) = y)$**

for Gaussian Random Process given Different Autocorrelation Functions

5. $X(t)$ is a wide sense stationary zero mean, Gaussian random processes with $R_{XX}(\tau) = 16 e^{\frac{-\pi\tau^2}{8}}$.

$Z(t) = X^2(t)$. This is the case of Gaussian noise as input to a square law detector.

- a. Find $E[Z(t)]$
- b. Find $R_{ZZ}(t_1, t_2)$
- c. Is $Z(t)$ a wide sense stationary random processes (YES or NO)?
- d. Is $Z(t)$ a Gaussian random processes (YES or NO)?

Hint: If X and Y are jointly Gaussian random variables then

$$E[X^2 Y^2] = E[X^2] E[Y^2] + 2 (E[XY])^2$$

6. A stationary discrete time random process $X[n]$ has an autocorrection function $R_{XX}[k]$. A random process $Y[n]$ is defined from $x[n]$ as $Y[n] = (-1)^n X[n]$.

- a. Find $R_{YY}[k]$ in terms of $R_{XX}[k]$.
- b. Is $Y[n]$ a wide sense stationary random process?
- c. Find $R_{XY}[k]$ in terms of $R_{XX}[k]$.
- d. Are $X[n]$ and $Y[n]$ jointly wide sense stationary?