

Special Problem II.B-1

The noise produced by a resistor at 270 degrees K is passed through a filter. At the output of the filter, the total noise power is found to be -90 dBm.

a) What is the bandwidth of the filter ??

b) How much noise power will appear at the filter output if the filter bandwidth is doubled ??